



**770.991.9299**  
 customercare@alarmassociates.net  
 3605 Flat Shoals Road  
 Atlanta, GA 30349

Honeywell Vista-Series & LYNX Plus  
**Keypad Trouble Displays**  
 (see manufacturer's published guide for complete instructions)

Keypad Trouble Message / Display			Condition	Action
Custom-Alpha (Vista Series)	Fixed-Word (Vista Series)	LYNX Plus (L3000)		
COMM. FAILURE	FC	FC	Landline communication failure to Central Station (if using landline communication)	Place System on Test with Central Station & test communication by tripping the alarm, allowing the siren to run for at least 15 seconds. If display continues, call 770-991-9299 for service.
TELCO FAULT	CHECK 94	---	Telephone line has a problem (if using landline communication)	If landline telephone service is NOT down, call 770-991-9299 for service.
AC LOSS	NO AC	No AC	System operating on Backup Battery	Ensure breaker is not tripped or transformer is not unplugged. Otherwise, call 770-991-9299 for service.
Rcvr Jam	CHECK 90	90	Wireless Device lost communication with Receiver	Clear trouble by entering 4-digit code + [OFF]. If trouble does not clear, call 770-991-9299 for service.
BELL FAILURE	CHECK 70	---	Connection problem between Siren & Control	
OPEN CIRCUIT	OC	---	Connection problem between Keypad & Control	
---	---	Fault 103	ECP Communication Failure	
Long Rng Trbl	bF	---	Wireless (cellular) communication signal lost (if using wireless communication)	
SYSTEM LO BAT	BAT (without zone #)	LowBat (without zone #)	System Low Battery	Call 770-991-9299 for service.
LO BAT (+ zone description)	BAT (+ zone #)	LowBat (+ zone #)	Wireless Device Low Battery	Replace Device Battery.
Busy-Standby	dl	dl	System is disabled	If displayed for longer than 1 minute, call 770-991-9299 for service.
CHECK or TRBL	91	---	Many potential issues.	If 974 or 975 are indicated, call your telephone service provider. Otherwise, call 770-991-9299 for service.
SUPV (+ zone description[s])	---	---	Indicates a problem on supervisory zone(s). Meaning that the operation of those zones may be compromised.	Determine if the zone(s) displayed can be corrected. If the problem has been corrected, disarm the alarm (4-digit code + OFF) to clear the "SUPV" display. If the display persists, call 770-991-9299 for service.
HSENS (+ zone #(s)) or LSENS (+ zone #(s))	---	---	This feature is only available on select panels. Indicates a smoke detector with problems, which may cause false alarms or not detect smoke.	Call 770-991-9299 for service.